

INDUSTRY PROCESS  
AND AUTOMATION SOLUTIONS




**BONFIGLIOLI**  
**RIDUTTORI**

# HDP

60 ... 90



**BONFIGLIOLI**




## SUMMARY

Chapter	Description	
<b>1</b>	<b>General information</b>	
1.1	Symbols and units of measurement	3
1.2	Product features	3
1.3	Installation	4
1.4	Maintenance	4
1.5	Storage	5
1.6	Conditions of supply	5
1.7	Paint coating	6
1.8	Selecting the gear unit	6
1.8.1	Engineering selection	7
1.8.2	Verifications	7
1.8.2.1	Shock loading	7
1.8.2.2	Motor mounting	8
1.8.2.3	Backstop device	8
1.8.2.4	Calculating the resulting overhung load	8
1.8.2.5	Overhung loading verification	9
1.8.2.6	Shaft loading	9
1.8.3	Lubrication	11
1.8.4	Service factor	12
1.8.5	Thermal capacity	14
1.8.6	Example	15
<b>2</b>	<b>Product configurations</b>	16
2.1	Ordering numbers	16
2.1.1	Base variants	16
2.1.2	Optional variants	17
2.2	Mounting position	18
2.3	Input and output configuration	18
2.3.1	Output configuration	18
2.3.2	Input configuration	18
2.3.3	Shaft arrangement	19
2.4	Motor availability	20
2.5	Optional variants	21
2.5.1	Auxiliary cooling devices	21
2.5.1.1	Fan cooling	21
2.5.1.2	Cooling coil	22
2.5.1.3	Heaters	22
2.5.2	Forced lubrication	23
2.5.2.1	Mechanical pump	23
2.5.2.2	Motor pump	24
2.5.3	Backstop device	25
2.5.4	Reinforced bearings	25
2.5.5	Seals and gaskets	26
2.5.6	Sensors	26
2.5.7	Drywell	26
2.5.8	Fixing elements	27
2.5.9	Certificates	28
<b>3</b>	<b>Gearbox rating charts</b>	29
3.1	HDP 60	29
3.2	HDP 70	29
3.3	HDP 80	30
3.4	HDP 90	30
3.5	Permitted overhung loads on output shaft	31
3.5.1	HDP 60	31
3.5.2	HDP 70	32
3.5.3	HDP 80	33
3.5.4	HDP 90	34
3.6	Permitted thrust load on output shaft	35
3.6.1	HDP 60	35
3.6.2	HDP 70	36
3.6.3	HDP 80	37
3.6.4	HDP 90	38
3.7	Mass moment of inertia	39
3.8	Exact ratios	39
<b>4</b>	<b>Dimensions and weight</b>	40
4.1	HDP 60	40
4.2	HDP 70	42
4.3	HDP 80	44
4.4	HDP 90	44
4.5	Manifold flange	48
4.6	Customer's shaft series HDP	48

### Revisions

Refer to page 50 for the catalogue revision index.

Visit [www.bonfiglioli.com](http://www.bonfiglioli.com) to search for catalogues with up-to-date revisions.




## PURE FORCE

Consistently high torque ratings, numerous close progression ratios, various mounting options along with compact dimensions to ease the application engineering to unmatched levels. The rigid monobloc gear case and the gears' high class of precision yield an extremely quiet and vibration-free operation. For more information:

[www.bonfiglioli.com](http://www.bonfiglioli.com)

 **BONFIGLIOLI**  
RIDUTTORI






## 1 GENERAL INFORMATION

### 1.1 SYMBOLS AND UNITS OF MEASUREMENT

Symb.	U.m.	Description	Symb.	U.m.	Description
$A_n_{1,2}$	[kN]	Permissible axial force	$M_r_{1,2}$	[Nm]	Torque demand
$f_s$	-	Service factor	$n_{1,2}$	[min <sup>-1</sup> ]	Speed
$i$	-	Gear ratio	$P_{1,2}$	[kW]	Power
$I$	-	Cyclic duration factor	$P_{n1,2}$	[kW]	Rated power
$J$	[Kgm <sup>2</sup> ]	Mass moment of inertia	$P_{r1,2}$	[kW]	Power demand
$M_{1,2}$	[Nm]	Torque	$R_c_{1,2}$	[kN]	Calculated radial force
$M_c_{1,2}$	[Nm]	Calculated torque	$R_{n1,2}$	[kN]	Permissible overhung load
$M_n_{1,2}$	[Nm]	Rated torque	$\eta$	-	Efficiency

<sub>1</sub> value applies to input shaft

<sub>2</sub> value applies to output shaft



## 1.2 PRODUCT FEATURES

Gear units of the HDP series make optimum use of advanced design features, to offer:

- Top torque density
- Superior performance
- Silent and vibration-free operation
- Total ruggedness and reliability
- Lifetime calculation in accordance with the applicable ISO and AGMA standards
- Extensive customisation through a wide range of options offered in the catalogue


The main construction features of the HDP parallel shaft gear unit range are:

- 4 frame sizes: HDP 60, HDP 70, HDP 80 and HDP 90 with 2 and 3 reduction stages
- Optimum distribution of rated torque values across the entire ratio range
- Gear ratios with 12% constant escalation
- Monobloc housing in rigid, nodular cast iron, paint coated both internally and externally. A modern design without recesses for easy cleaning. Universal mounting thanks to the many machined surfaces. Profiles and dimensions optimised by FEM analysis for superior structural rigidity, low acoustic emissions and a moderate weight.
- Casehardened and hardened alloy steel helical gears with ground profile, optimised for:
  - more silent operation and smoother transmission of input gears
  - maximum transmissible torque of the final reductions
- Input shafts generally casehardened and ground finished. Output shafts from hardened and tempered alloy steel.
- Input shaft configurations:
  - solid, single or double-sided shaft with dimensions to UNI/ISO 775-88 (extended length)
  - direct motor mounting or lantern housing and flexible coupling provision
- Output shaft configurations:
  - solid, single or double-sided shaft with dimensions to UNI/ISO 775-88 (extended length)
  - hollow shaft with keyway
  - hollow shaft with shrink disc
- Heavy duty taper roller bearings from the most reputed brands for unparalleled overhung load capacity that can be further increased through the reinforced "HDB" bearing option.
- A wide range of customisation options are available upon request, including:
  - auxiliary cooling/heating devices
  - forced lubrication systems
  - backstop device
  - mounting or manifold flanges
  - bearings for increased overhung load capacity
  - seals of different types and materials
  - sensors
  - dry-well device for vertical shaft installations
  - fixing elements

## 1.3 INSTALLATION

The following installation instructions must be observed:

- Make sure that the gearbox is correctly secured to avoid vibrations.  
If shocks or overloads are expected, install hydraulic couplings, clutches, torque limiters, etc.
- Before being painted, the machined surfaces and the outer face of the oilseals must be protected to prevent paint drying out the rubber and jeopardising the oil-seal function.
- Parts fitted on the gearbox output shaft must be machined to ISO H7 tolerance to prevent interference fits that could damage the gearbox itself. Further, to mount or remove such parts, use suitable pullers or extraction devices using the tapped hole located at the top of the shaft



extension.

- Mating surfaces must be cleaned and treated with suitable protective products before mounting to avoid oxidation and, as a result, seizure of parts.
- Prior to putting the gear unit into operation make sure that the equipment that incorporates the same complies with the current revision of the Machines Directive 89/392.
- Before starting up the machine, make sure that oil level conforms to the mounting position specified for the gear unit.
- For outdoor installation provide adequate guards in order to protect the drive from rainfalls as well as direct sun radiation.

## 1.4 MAINTENANCE

It is advisable to change the lubricant after the initial 300 hours of operation and thoroughly clean the interior of the unit with a suitable detergent.

Do not mix different types and/or brands of oil.


Periodically check the oil level, and replace at the intervals given in the chart.

Oil temperature [°C]	Oil change interval [h]	
	mineral oil	synthetic oil
< 65	8000	25000
65 - 80	4000	15000
80 - 95	2000	12500

## 1.5 STORAGE

Observe the following instructions to ensure correct storage of the products:

- Do not store outdoors, in areas exposed to weather or with excessive humidity.
- Always place boards, wood or other material between the products and the floor.  
The gearboxes should not have direct contact with the floor.
- In case of long-term storage all machined surfaces such as flanges, shafts and couplings must be coated with a suitable rust inhibiting product (Mobilarma 248 or equivalent).  
Furthermore gear units must be placed with the fill plug in the highest position and filled up with oil. Before putting the units into operation the appropriate quantity, and type, of oil must be restored.



---


## 1.6 CONDITIONS OF SUPPLY

Gear units are supplied as follows:

- configured for installation in the mounting position specified when ordering;
- tested to manufacturer specifications;
- mating machined surfaces come unpainted;
- nuts and bolts for mounting motors are provided;
- shafts are protected during transportation by plastic caps.

## 1.7 PAINT COATING

Internal and external paint coating with thermosetting epoxy resin and polyester-based powder with a high corrosion protection rating, also suitable for outdoor installation. Colour is grey RAL 7042.  
It can be top-coated with synthetic paints.



## 1.8 SELECTING THE GEAR UNIT

### 1.8.1 ENGINEERING SELECTION

1. First determine the gear ratio:

$$i = \frac{n_1}{n_2}$$

2. Calculate the power  $P_{r1}$  required at the input shaft:

$$P_{r1} = \frac{P_{r2}}{\eta}$$

	$\eta$
2x	0.96
3x	0.94

3. Determine the applicable service factor  $f_s$  and the adjusting factor  $f_m$  depending on prime mover:

	$f_m$
Electric motor	1.00
Hydraulic motor	1.00
Turbine	1.00
Multi-cylinder internal combustion engine	1.25
Single cylinder internal combustion engine	1.50

4. Use the rating charts to select the gear unit with the gear ratio nearest to that calculated, and with a rated power  $P_{n1}$ , so that:

$$P_{n1} \geq P_{r1} \times f_s \times f_m$$

### 1.8.2 VERIFICATIONS


#### 1.8.2.1 SHOCK LOADING

For intermittent duty, impact/shock loading applications or start-ups under full load or with high inertial loads, make sure the following condition is satisfied for momentary peak torque  $M_p$  generated during the operating cycle:

$$M_p \leq M_{n2} \times f_p$$

		$f_p$				
		1	2 ... 10	11 ... 50	51 ... 100	> 100
Drive	Constant direction	2.0	1.6	1.3	1.1	1.0
	Reversals	1.4	1.2	0.9	0.8	0.7

If the above condition is not satisfied, consider installing a torque limiter or selecting a gear unit of the next size up.



### 1.8.2.2 MOTOR MOUNTING

Verify that the appropriate motor adapter is available for the selected gear unit. See section [2.4](#). Because of standardisation, the rated power of the electric motor selected might be greater than power  $P_{r1}$ , actually requested by the application. Make sure that the electric motor will never develop the extra power at any stage of the operating cycle. If you have any doubts about the validity of the application data, or uncertainty concerning the actual load pattern, install a torque limiting device or proportionally revise the applicable service factor.

### 1.8.2.3 BACKSTOP DEVICE

If the gear unit is specified with a backstop, verify the load capacity of the device in the relevant section of this catalogue and make sure the torque  $M_{1MAX}$  is never exceeded in operation.

### 1.8.2.4 CALCULATING THE RESULTING OVERHUNG LOAD

External transmissions keyed onto input and/or output shaft generate loads that act radially onto same shaft.


Resulting shaft loading must be compatible with both the bearing and the shaft capacity.

Namely shaft loading ( $R_{c1}$  for input shaft,  $R_{c2}$  for output shaft), must be equal or lower than admissible overhung load capacity for shaft under study ( $R_{x1}$  for input shaft,  $R_{x2}$  for output shaft). OHL capability listed in the rating chart section.


In the formulas given below, index (1) applies to parameters relating to input shaft, whereas index (2) refers to output shaft.

The load generated by an external transmission can be calculated with close approximation by the following equation:

$R_c = \frac{2000 \times M \times K_r}{d}$	
$K_r = 1$	
$K_r = 1.25$	
$K_r = 1.5 - 2.0$	
$M$ [Nm]	
$d$ [mm]	



### 1.8.2.5 OVERHUNG LOADING VERIFICATION



	$K_1$							
$x$ [mm] =	-50	-25	0	25	50	75	100	150
<b>HDP 60</b>	-	1.10	1.00	0.77	0.62	0.52	0.45	-
<b>HDP 70</b>	-	1.10	1.00	0.77	0.62	0.52	0.45	-
<b>HDP 80</b>	1.17	1.08	1.00	0.81	0.68	0.54	0.44	0.32
<b>HDP 90</b>	1.15	1.07	1.00	0.83	0.72	0.61	0.50	0.37

	$K_2$											
$x$ [mm] =	-100	-75	-50	-25	0	25	50	75	100	150	200	250
<b>HDP 60</b>	-	-	1.20	1.09	1.00	0.74	0.58	0.48	0.41	0.32	-	-
<b>HDP 70</b>	-	1.34	1.20	1.09	1.00	0.77	0.63	0.53	0.46	0.36	0.30	-
<b>HDP 80</b>	1.38	1.26	1.16	1.07	1.00	0.82	0.69	0.59	0.52	0.42	0.35	0.30
<b>HDP 90</b>	1.33	1.23	1.14	1.07	1.00	0.81	0.68	0.58	0.51	0.41	0.34	0.30

### 1.8.2.6 SHAFT LOADING

#### 1. Overhung loads on output shaft

Refer to section [3.5.1](#), and verify that both the radial and the axial force acting onto output shaft do not exceed the maximum permitted for the selected product configuration. In addition to overhung load, thrust load may also be applied:


$$An_2 \leq 0.2 \times Rn_2.$$

The HDB option provides higher capacity bearings to cater for particularly heavy external loads. If external loads exceed the capacity of even the heavy-duty bearings, consider providing external support for the drive shafts, reducing external loads or, if necessary, selecting a gear unit of the next size up.

When checking the overhung load capacity refer to scheme shown at paragraph [1.8.2.5](#). Calculate the admissible overhung load  $R_x$  that is relevant to the distance the force applies from shaft midpoint and compare this with the force  $R_c$  that acts onto the shaft.

Multiply the nominal radial load  $Rn_2$ , as listed in the technical data section, for the load location factor  $K_2$  to get the permissible overhung load  $Rx_2$  for the output shaft.

Rated overhung loads  $Rn$  are calculated for the most unfavourable condition as far as direction of rotation and the angle the force applies onto the shaft. Catalogue values are therefore conservative, for an in-depth calculation contact the Technical Service of



Bonfiglioli Riduttori.

When a radial force applies a thrust load  $An_2 \leq 0.2 \times Rn_2$  is also permitted.

## 2. Thrust loads on output shaft

Refer to section [3.6.1](#) and verify that thrust force on the shaft does not exceed that specified in the chart for the selected product configuration and combination of direction of shaft rotation / direction of force.

If an overhung load is present in addition to the thrust load, contact Bonfiglioli Riduttori's Technical Service.

Permissible thrust loads refer exclusively to forces applying axially on the shaft. In case of forces applying offset please consult with Bonfiglioli's Technical Service.

## 3. Overhung and thrust loads on input shaft

When checking the overhung load capacity refer to scheme shown at paragraph [1.8.2.5](#).


Calculate the admissible overhung load  $Rx$  that is relevant to the distance the force applies from shaft midpoint and compare this with the force  $Rc$  that acts onto the shaft.

Multiply the nominal radial load  $Rn_1$ , as listed in the technical data section, for the load location factor  $K_1$  to get the permissible overhung load  $Rx_1$  for the output shaft.


Rated overhung loads  $Rn$  are calculated for the most unfavourable condition as far as direction of rotation and the angle the force applies onto the shaft. Catalogue values are therefore conservative, for an in-depth calculation contact the Technical Service of Bonfiglioli Riduttori.

When a radial force applies a thrust load  $An_1 \leq 0.2 \times Rn_1$  is also permitted.

For gear units with double extended shafts (configurations LD, RD and DD) the permitted overhung load charted refers to shaft end highlighted in black in the scheme here below:



If an overhung load is applied to both shaft ends, contact Bonfiglioli Riduttori's Technical Service for advise.



### 1.8.3 LUBRICATION

Internal parts of HDP gear units are oil bath and splash lubricated. Upper bearings in the V5 mounting position are grease lubricated. In this case a Nilos ring retains the grease, unless forced lubrication by mechanical pump (OP1 and OP2 options) or motor pump (MOP option) is specified in the order.

The gear units are supplied without lubricant. It is the customer's responsibility to fill the unit with the appropriate quantity of oil before start-up.

**The quantities of lubricant given in the chart are indicative. Refer to the sight glass' centre line, or the dipstick if supplied, for correct filling.**


**The quantity of lubricant given in the chart may vary, sometimes substantially, depending on the gear ratio or a particular product modification.**

	B3	B6	[I] B7	V5
<b>HDP 60</b>	10.0	14.8	14.6	16.0
<b>HDP 70</b>	10.5	15.5	15.3	16.7
<b>HDP 80</b>	16.1	23.8	23.5	25.6
<b>HDP 90</b>	22.9	33.8	33.4	36.5

Lubricant	kinematic viscosity at 40°C [cst]			
	ISO VG 220	ISO VG 320	ISO VG 460	
<b>Mineral Oil (EP additives)</b>	Tamb	0°C ... 20°C	10°C ... 40°C	20°C ... 50°C
<b>Synthetic oil</b>	Tamb	0°C ... 30°C	10°C ... 50°C	-

Lubricant must be pre-heated through the appropriate electric resistance (HE option) in the following cases:

- operation at ambient temperatures lower than 0°C
- upon starting up gear units that are oil-bath and splash lubricated if the difference between the ambient temperature and the oil's pour point is greater than 10°C
- Upon starting up gear units with forced lubrication systems (options OP1, OP2 or MOP) if the oil viscosity exceeds 1800 cst. Depending of the type of lubricant used, this value may be produced with ambient temperatures between 10°C and 20°C approx.




## 1.8.4 SERVICE FACTOR

Service factors listed here under are empirical values based on AGMA and ISO specifications as well as our experience for use in common applications. They apply for state of the art-designed driven machines and normal operating conditions.


Application	≤ 10 hrs/day	> 10 hrs/day	Application	≤ 10 hrs/day	> 10 hrs/day
<b>Agitators, mixers</b>			<b>Fans</b>		
Pure liquids	1.25	1.50	Centrifugal	1.00	1.25
Liquids and solids	1.25	1.50	Cooling towers	2.00	2.00
Liquids - variable density	1.50	1.75	Forced draft	1.25	1.25
<b>Blowers</b>			Induced draft	1.50	1.50
Centrifugal	1.00	1.25	Industrial and mine	1.50	1.50
Lobe	1.25	1.50			
Vane	1.25	1.50			
<b>Clarifiers</b>	1.00	1.25			
<b>Clay working machinery</b>					
Brick press	1.75	2.00			
Briquette machine	1.75	2.00			
Pug mill	1.25	1.50			
<b>Compactors</b>	2.00	2.00			
<b>Compressors</b>					
Centrifugal	1.25	1.50			
Lobe	1.25	1.50			
Reciprocating, multi-cylinder	1.50	1.75			
Reciprocating, single-cylinder	1.75	2.00			
<b>Conveyors -general purpose</b>					
Uniformly loaded or fed	1.15	1.25			
- Heavy duty					
Not uniformly fed	1.25	1.50			
- Reciprocating or shaker	1.75	2.00			
<b>Cranes (*)</b>					
<b>Dry dock</b>					
Main hoist	2.50	2.50			
Auxiliary hoist	2.50	3.00			
Boom hoist	2.50	3.00			
Slewing Drive	2.50	3.00			
Traction Drive	3.00	3.00			
<b>Trolley Drive</b>					
Gantry Drive	3.00	3.00			
Traction Drive	2.00	2.00			
<b>Industrial duty</b>					
Main hoist	2.50	3.00			
Auxiliary hoist	2.50	3.00			
Bridge and	3.00	3.00			
Trolley travel	3.00	3.00			
<b>Crusher</b>					
Stone or ore	2.00	2.00			
<b>Dredges</b>					
Conveyors	1.25	1.50			
Cutter head drives	2.00	2.00			
Screen drives	1.75	2.00			
Stackers	1.25	1.50			
Winches	1.25	1.50			
<b>Elevators</b>					
Bucket	1.25	1.50			
Centrifugal discharge	1.15	1.25			
Escalators	1.15	1.25			
Freight	1.25	1.50			
Gravity discharge	1.15	1.25			
<b>Extruders</b>					
General	1.50	1.50			
<b>Plastics</b>					
Variable speed drive	1.50	1.50			
Fixed speed drive	1.75	1.75			
<b>Rubber</b>					
Continuous screw operation	1.75	1.75			
Intermittent screw operation	1.75	1.75			
<b>Fans</b>					
Centrifugal					
Cooling towers					
Forced draft					
Induced draft					
Industrial and mine					
<b>Feeders</b>					
Apron					
Belt					
Disc					
Reciprocating					
Screw					
<b>Food industry</b>					
Dough mixer					
Meat grinders					
Slicers					
<b>Generators and excitors</b>					
<b>Hammer mills</b>					
<b>Hoists (*)</b>					
Heavy duty					
Medium duty					
Skip hoist					
<b>Lumber industry</b>					
Barkers - spindle feed					
Main drive					
Conveyors - burner					
Main or heavy duty					
Main log					
Re-saw, merry-go-round					
<b>Conveyors</b>					
Slab					
Transfer					
<b>Chains</b>					
Floor					
Green					
<b>Cut-off saws</b>					
Chain					
Drag					
Debarking drums					
<b>Feeds</b>					
Edger					
Gang					
Trimmer					
Log deck					
Log hauls - incline - weel type					
Log turning devices					
Planer feed					
Planer tilting hoists					
Rolls - live-off brg. - roll cases					
Sorting table					
Tipple hoist					
<b>Transfers</b>					
Chain					
Craneways					
Tray drives					
Veneer lathe drives					
<b>Metal mills</b>					
Slab pushers					
Shears					
Wire drawing					
Wire winding machine					

(\*) - Indication of service factor based on FEM 1.001 classification available upon request. Consult factory.

- hoists for passengers lift: charted values **not applicable**. Consult factory.



Application	≤ 10 hrs/day	> 10 hrs/day	Application	≤ 10 hrs/day	> 10 hrs/day
<b>Mills, rotary type</b>			<b>Plastics industry</b>		
Ball and rod	2.00	2.00	Batch mixers	1.75	1.75
Spur ring gear	2.00	2.00	Continuous mixers	1.50	1.50
Helical ring gear	1.50	1.50	Compounding mill	1.25	1.25
Direct connected	2.00	2.00	Calendars	1.50	1.50
Cement kilns	1.50	1.50	Secondary processing		
Dryers and coolers	1.50	1.50	Blow molders	1.50	1.50
<b>Mixers</b>			Coating	1.25	1.25
Concrete	1.50	1.75	Film	1.25	1.25
<b>Paper mills</b>			Pre-plasticizers	1.50	1.50
Agitator (mixer)	1.50	1.50	Rods	1.25	1.25
Agitator for pure liquors	1.25	1.25	Sheet	1.25	1.25
Barking drums	2.00	2.00	Tubing	1.25	1.50
Barkers - mechanical	2.00	2.00	<b>Pumps</b>		
Beater	1.50	1.50	Centrifugal	1.15	1.25
Breaker stack	1.25	1.25	<b>Reciprocating</b>		
Calendar	1.25	1.25	Single acting, three or more cylinders	1.25	1.50
Chipper	2.00	2.00	Double acting, two or more cylinders	1.25	1.50
Chip feeder	1.50	1.50	<b>Rotary</b>		
Coating rolls	1.25	1.25	Gear type	1.15	1.25
<b>Conveyors</b>			Lobe	1.15	1.25
Chip, bark, chemical	1.25	1.25	Vane	1.15	1.25
Log (including slab)	2.00	2.00	<b>Rubber industry</b>		
Couch rolls	1.25	1.25	<b>Intensive internal mixer</b>		
Cutter	2.00	2.00	Batch mixers	1.75	1.75
Cylinder molds	1.25	1.25	Continuous mixers	1.50	1.50
<b>Dryers</b>			Refiner - two rolls	1.50	1.50
Paper machine	1.25	1.25	Calendars	1.50	1.50
Conveyors type	1.25	1.25	<b>Sand muller</b>	1.25	1.50
Embosser	1.25	1.25	<b>Sewage disposal equipment</b>		
Extruder	1.50	1.50	Aerators	2.00	2.00
Jordan	1.50	1.50	Chemical feeders	1.25	1.25
Kiln drive	1.50	1.50	Dewatering screens	1.50	1.50
Paper rolls	1.25	1.25	Scum breakers	1.50	1.50
Platter	1.50	1.50	Slow or rapid mixers	1.50	1.50
Presses - felt and suction	1.25	1.25	Sludge collectors	1.25	1.25
Pulper	2.00	2.00	Thickeners	1.50	1.50
Pumps - vacuum	1.50	1.50	Vacuum filters	1.50	1.50
Reel (surface type)	1.25	1.25	<b>Screens</b>		
<b>Screens</b>			Air washing	1.00	1.25
Chip	1.50	1.50	Rotary - stone or gravel	1.25	1.50
Rotary	1.50	1.50	Travelling water intake	1.00	1.25
Vibrating	2.00	2.00	<b>Sugar industry</b>		
Size press	1.25	1.25	Beet slicer	2.00	2.00
Super calendar	1.25	1.25	Cane knives	1.50	1.50
Thickener (AC motor)	1.50	1.50	Crushers	1.50	1.50
Thickener (DC motor)	1.25	1.25	Mills (low speed end)	1.75	1.75
Washer (AC motor)	1.50	1.50	<b>Textile machinery</b>	1.25	1.50
Washer (DC motor)	1.25	1.25			
Wind and unwind stand	1.25	1.50			
Winders (surface type)	1.25	1.25			
Yankee dryers	1.25	1.25			



## 1.8.5 THERMAL CAPACITY

Checking the thermal capacity may not be necessary if the gear unit operates continuously for less than 3 hours followed by a rest time sufficient to restore the ambient temperature.

$$P_{r1} \leq (P_T \times f_{TA} \times f_{AMB} \times f_{ALT} - P_{T0} \times f_i \times f_{n1}) \times f_{INT} + P_{FAN} \times f_{TA} \times f_{ALT} + P_{SR}$$

Reference values


Symbol	Definition
$P_T$	Base thermal capacity
$P_{T0}$	Equivalent thermal capacity under no load
$P_{SR}$	Additional thermal capacity linked to the use of the cooling coil
$P_{FAN}$	Additional thermal capacity linked to fan cooling

Adjusting factors

Symbol	Relationship
$f_i$	factor depends on nominal gear ratio [ $i_N$ ]
$f_{n1}$	factor depends on drive speed $n_1$ . Interpolate for intermediate speed values
$f_{TA}$	factor depends on ambient temperature $t_a$ . Interpolate for intermediate values
$f_{INT}$	factor depends on the operating cycle per hour [ED%]. Interpolation is permitted
$f_{AMB}$	factor depends on the type of ambient the gear unit is installed into
$f_{ALT}$	factor depends on the altitude the gear unit operates at. Interpolation is permitted

		HDP 60				HDP 70				HDP 80				HDP 90			
		B3	B6	B7	V5												
$P_T$ [kW]	2x	46	49	49	43	48	52	52	45	63	69	69	60	83	90	90	78
	3x	32	34	34	29	33	36	36	31	44	47	47	41	57	62	62	54
$P_{T0}$ [kW]	2x	16	26	34	31	18	35	40	34	10	56	63	57	14	82	93	79
	3x	9	11	13	10	10	12	14	12	11	19	21	17	15	27	29	23
$P_{SR}$ [kW]	2x	32	32	18	17	32	32	17	18	41	41	23	27	48	39	27	30
	3x	18	18	9	10	18	18	8	10	28	28	16	18	22	22	8	14

	$n_1$ [min <sup>-1</sup> ]	HDP 60			HDP 70			HDP 80			HDP 90		
		900	1100	1400	900	1100	1400	900	1100	1400	900	1100	1400
$P_{FAN}$	2x	10	13	15	10	13	15	19	24	27	22	28	32
	3x	7	9	10	7	9	10	13	16	18	15	19	22



$i_N$	$f_i$	$n_1 [\text{min}^{-1}]$			
2x 	7.1	1.00	500	900	1100
	8.0	1.00		0.63	0.78
	9.0	1.00			1.00
	10.0	0.85			
	11.2	0.85			
	12.5	0.73			
	14.0	0.73			
	16.0	0.64			
	18.0	0.64			
	20.0	0.55			
3x 	22.4	0.55			
	22.4	1.00			
	25.0	1.00			
	28.0	1.00			
	31.5	0.95			
	35.5	0.95			
	40.0	0.90			
	45.0	0.90			
	50.0	0.83			
	56.0	0.83			
	63.0	0.56			
	71.0	0.56			
	80.0	0.49			
	90.0	0.49			
	100.0	0.47			
	112.0	0.47			
$f_{n1}$		500	900	1100	1400
$f_{TA}$		0.34	0.63	0.78	1.00
$f_{AMB}$		10 °C	20 °C	30 °C	40 °C
$f_{AMB}$		1.14	1.00	0.86	0.71
$f_{AMB}$		50 °C	0.57		
$f_{INT}$		small confined space $v = 0.5 \text{ m/s}$	large indoor space $v = 1.4 \text{ m/s}$	outdoors $v = 4 \text{ m/s}$	
$f_{INT}$		0.75	1.00	1.30	
$f_{ALT}$		100%	80%	60%	40%
$f_{ALT}$		1.00	1.05	1.20	1.35
$f_{ALT}$		20%	1.80		
$f_{ALT}$		Operating cycle per hours [%]			
$f_{ALT}$		100%	80%	60%	40%
$f_{ALT}$		0	1000	2000	3000
$f_{ALT}$		1.00	0.93	0.87	0.81

### 1.8.6 EXAMPLE

Application data		Environmental conditions	
$n_1 = 900 \text{ min}^{-1}$		Ambient temperature = 30°C	$f_{AMB} = 1$
$n_2 = 75 \text{ min}^{-1}$		large indoor space	$f_{TA} = 0.86$
$f_s = 2$		altitude m.s.l.m. = 0 m	$f_{ALT} = 1$
$P_{r2} = 25 \text{ kW}$			
Mounting position: B7			
Operating cycle per hours: 100% ---> $f_{INT} = 1$			

Product selection:

$$\begin{aligned} i &= n_1 / n_2 = 12 \rightarrow i_N = 12 \\ P_{r1} &= P_{r2} / \eta = 26 \rightarrow P_{r1} = 26 \text{ kW} \\ P_{n1} &\geq P_{r1} \times f_s = 52 \rightarrow P_{n1} \geq 52 \text{ kW} \end{aligned}$$

Ordering numbers:

HDP 70 2 11.7 LP LR VP B7

Thermal capacity check:

$n_1 = 900 \text{ min}^{-1}$	$f_{n1} = 0.63$
HDP 70 2...B7	$P_T = 52 \text{ kW}$
HDP 70 2...B7	$P_{T0} = 40 \text{ kW}$
$i_N = 12$	$f_i = 0.85$


$$P_{r1} \leq (P_T \times f_{TA} \times f_{AMB} \times f_{ALT} - P_{T0} \times f_i \times f_{n1}) \times f_{INT} + P_{FAN} \times f_{TA} \times f_{ALT} = 23.3 \text{ kW} < 26 \text{ kW} \triangleleft$$

Option 1 - Fan cooling HDP 70 2 --->  $P_{FAN} = 10 \text{ kW}$

$$P_{r1} \leq (P_T \times f_{TA} \times f_{AMB} \times f_{ALT} - P_{T0} \times f_i \times f_{n1}) \times f_{INT} + P_{FAN} \times f_{TA} \times f_{ALT} = 31.9 \text{ kW} > 26 \text{ kW} \smile$$

Option 2 - Cooling coil HDP 70 2 ... B7 --->  $P_{SR} = 17 \text{ kW}$


$$P_{r1} \leq (P_T \times f_{TA} \times f_{AMB} \times f_{ALT} - P_{T0} \times f_i \times f_{n1}) \times f_{INT} + P_{SR} = 40.3 \text{ kW} > 26 \text{ kW} \smile$$




## 2 PRODUCT CONFIGURATIONS


### 2.1 ORDERING NUMBERS

#### 2.1.1 BASE VARIANTS







## 2.1.2 OPTIONAL VARIANTS



REMARK: The multiple selection of some of the variants may be subject to technical or dimensional constraints. Consult with the factory to have your selection approved.




## 2.2 MOUNTING POSITION



## 2.3 INPUT AND OUTPUT CONFIGURATION


### 2.3.1 OUTPUT CONFIGURATION




### 2.3.2 INPUT CONFIGURATION



















On the input side the gear unit can be arranged in either one of the configurations described here after:


- **Solid input shaft**, single- or double-sided – Specify **VP**
- **Motor flange mounting** for an IEC-standard electric motor with IM B5 flange. Drive is transmitted via the gear unit's keyed hollow input shaft. The option is only applicable to units HDP 60... HDP 90 in the triple reduction configuration – Specify **AD**.
- **Motor mounting through bell housing and flexible coupling**. The option is designated **GL** or **GR** depending on what side of the gear unit the coupling is mounted. The flexible coupling is within the scope for supply.





### 2.3.3 SHAFT ARRANGEMENT

	VP - GL - AD	VP - GR - AD	VP - GL - GR
LP	 LL	 LR	 LD
	 RL	 RR	 RD
	 DL	 DR	 DD
H	 LL	 LR	 LD
	 LL	 LR	 LD
S	 RL	 RR	 RD
	 RL	 RR	 RD




## 2.4 MOTOR AVAILABILITY

The following charts list the motor/gearbox combinations that are geometrically feasible. Variants are only applicable if either an AD (direct motor mounting) or a GL / GR input configuration (coupling through bell housing and flexible coupling) were previously specified within the ordering code.

Because of standardisation, the rated power of the electric motor selected might be greater than power  $P_{r1}$  actually requested by the application. Make sure that the electric motor will never develop the extra power at any stage of the operating cycle. If you have any doubts about the validity of the application data, or uncertainty concerning the actual load pattern, install a torque limiting device or proportionally revise the applicable service factor.

	Input configuration AD						
	112	132	160	180	200	225	250
HDP 60 3	x	x	x	x			
HDP 70 3	x	x	x	x	x		
HDP 80 3		x	x	x	x		
HDP 90 3			x	x	x		

	Input configuration GL - GR						
	132	160	180	200	225	250	280
HDP 60 2	17.3_19.4	7.1_19.4	7.1_19.4	7.1_19.4	7.1_19.4		
HDP 60 3	22.7_98.4	22.7_98.4	22.7_49.1	22.7_49.1	22.7_49.1		
HDP 70 2	19.4_22.6	8.0_22.6	8.0_22.6	8.0_22.6	8.0_22.6		
HDP 70 3	25.5_114.4	25.5_114.4	25.5_57.0	25.5_57.0	25.5_57.0		
HDP 80 2		15.5_22.6	15.5_22.6	15.5_22.6	8.1_22.6	8.1_22.6	8.1_22.6
HDP 80 3		25.8_111.4	25.8_111.4	25.8_75.2	25.8_75.2	25.8_75.2	25.8_75.2
HDP 90 2		15.8_22.4	15.8_22.4	15.8_22.4	15.8_22.4	7.9_22.4	7.9_22.4
HDP 90 3		25.4_110.1	25.4_110.1	25.4_110.1	25.4_73.3	25.4_73.3	25.4_73.3




## 2.5 OPTIONAL VARIANTS

### 2.5.1 AUXILIARY COOLING DEVICES


#### 2.5.1.1 FAN COOLING

If the **FAN** option is specified, a cooling fan is keyed to the end of the input shaft opposite the drive side. This option is not available with other configurations that use the same shaft end and with variants MOP - forced lubrication with motor pump - and LAB - labyrinth oil seals. The increased cooling effect obtained by this option is shown by the thermal capacity value  $P_{FAN}$ . See the section, [1.8.5](#).

The efficiency of the fan is greatly reduced at drive speed lower than  $n_1 = 900 \text{ min}^{-1}$ . Should this be the case the cooling coil is recommended instead as the device that best increases the heat dissipation when the mechanical power is greater than thermal capacity.



	A	B	C	D
<b>HDP 60_FAN</b>	125	130	255	200
<b>HDP 70_FAN</b>	125	130	255	200
<b>HDP 80_FAN</b>	155	155	348	235
<b>HDP 90_FAN</b>	178	178	360	260




### 2.5.1.2 COOLING COIL

The cooling coil option **SR** is designed for integration in a cooling circuit to be provided by the installer. The water supply circuit must correspond to the following specifications: maximum pressure 8 bar, flow rate 5 l/min, maximum delivery temperature 20°C.

The increased cooling effect obtained in these conditions is shown by the thermal capacity value  $P_{SR}$ .


See the section, [1.8.5](#).



	A	B
HDP 60_SR	147	170
HDP 70_SR	147	170
HDP 80_SR	173	190
HDP 90_SR	190	210

### 2.5.1.3 HEATERS


In very low ambient temperatures it may prove necessary to pre-heat the lubricant in the sump before start-up and/or during operation. The **HE** option envisages the installation of an electrical heating element, supplied with a thermostat to detect when the minimum temperature needed for correct operation has been reached. The wiring necessary for the thermostat must be provided by the installer.



## 2.5.2 FORCED LUBRICATION

### 2.5.2.1 MECHANICAL PUMP

In continuous duty applications and V5 mounting position installations, an optional forced lubrication circuit is available on request, complete with a pump keyed to the shaft end opposite the drive side. This system ensures adequate lubrication of the top bearings. When ordering, specify the pump type - **OP1** or **OP2** – to suit drive speed  $n_1$ . See the table below. This option is not available with other configurations that use the same shaft end.




- 1 - Pump
- 2 - Filter
- 3 - Oil flow visual indicator

	$n_1 = 900 \text{ min}^{-1}$	$n_1 = 1100 \text{ min}^{-1}$	$n_1 = 1400 \text{ min}^{-1}$
HDP	OP2	OP2	OP1
	A	B	
<b>HDP 60_OP1</b>	190	105	
<b>HDP 60_OP2</b>	190	105	
<b>HDP 70_OP1</b>	215	105	
<b>HDP 70_OP2</b>	215	105	
<b>HDP 80_OP1</b>	240	105	
<b>HDP 80_OP2</b>	240	130	
<b>HDP 90_OP1</b>	240	130	
<b>HDP 90_OP2</b>	240	130	

The chart shows the applicability for the pump depending on the input and output configuration.


	LL RD DL	LR RR DR	LD RD DD
LP	—	VP GR AD	—
H	—	VP GR AD	—
S	—	VP GR AD	—



## 2.5.2.2 MOTOR PUMP

For intermittent duty applications and V5 mounting position installations, a forced lubrication circuit is available on request, complete with an independently powered motor pump. This system ensures a constant oil flow to the top bearings. Specify the **MOP** option.

Option MOP is not available if fan cooling - option FAN - is also specified.



1 - Motorpump


2 - Filter

3 - Minimum pressure switch

	A	B	C
HDP 60_MOP	190	225	310
HDP 70_MOP	215	225	330
HDP 80_MOP	240	270	355
HDP 90_MOP	240	285	390

The chart shows the applicability for the motorpump depending on the input and output configuration.

	LL RL DL	LR RR DR	LD RD DD
LP	VP	VP GR AD	VP GR
H	VP	VP GR AD	VP GR
S	VP	VP GR AD	VP GR



### 2.5.3 BACKSTOP DEVICE

The backstop device ensures that only one direction of rotation is allowed, and prevents the gearbox to be backdriven by the load connected to the output shaft.


In addition to verifying the shock loads shown in section [1.8.2.1](#), also make sure that the torque transmitted to the backstop  $M_1 = M_2 / (i \times \eta)$  is less than the admissible torque  $M_{1\max}$  listed in the chart below.

A drive speed  $n_1 \geq 800 \text{ min}^{-1}$  will ensure the optimal operation for the device.

The backstop is keyed to the input shaft opposite the drive end and it is accessible for inspection.

Along with the specification of the backstop device, option **A**, the direction of free rotation for the output shaft (**CW** or **CCW**) must also be specified in the order.

This option is not available with other configurations that use the same shaft end.




	i	A	B	$M_{1\max}$ [Nm]
HDP 60_A	7.1 ... 15.2	125	202.5	800
	17.3 ... 98.4	100	197.5	375
HDP 70_A	8.0 ... 17.7	125	202.5	800
	19.4 ... 114.4	100	197.5	375
HDP 80_A	8.1 ... 22.6	130	233	912
	25.8 ... 111.4	110	228	550
HDP 90_A	7.9 ... 22.4	150	261	1400
	25.4 ... 110.1	125	256	800

### 2.5.4 REINFORCED BEARINGS

Optional heavy-duty bearings are also available, with increased overhung load capacity. The **HDB** option can only be applied to units with an LP version solid output shaft.

See the relevant section in this catalogue for precise overhung load values.

Option cannot be specified along with variants DW -drywell- or LAB -labyrinth seals-.



## 2.5.5 SEALS AND GASKETS

On request, gearboxes can be equipped with different oil sealing systems. These are:

**LAB** – Standard oil seals on each shaft are replaced by non-contacting seals, labyrinth type, that are wear- and maintenance-free. The option only applies to configurations featuring solid input shaft, type VP, exclusively in the B3 mounting position.

Option cannot be specified along with variants FAN -fan cooling-, HDB -reinforced bearings- and OLG - oil level indicator.

**VS** – Viton® compound seal rings

**DS** – Dual set of seal rings at each shaft end

**DVS** – Dual set of Viton® compound seal rings at each shaft end.

## 2.5.6 SENSORS

**Bimetal thermostat** – If the **TG** option is specified, a bimetal thermostat is supplied to prevent the oil to exceed the set temperature of  $90^{\circ}\text{C} \pm 5^{\circ}\text{C}$ . The device is supplied with the gear unit, but installation and wiring are the responsibility of the installer.

**Oil level indicator** – If the **OLG** option is specified, the gearbox is supplied with a device permitting remote control of the oil level. The device best operates when the gearbox is idle and should be bypassed when the gearbox is operating. Wiring is the responsibility of the installer.

Variant not available along with the DW -dry well- and LAB -labyrinth seals-

## 2.5.7 DRYWELL

The “drywell” device, option **DW**, is only available for the V5 vertical mounting position, and ensures the oil-tightness of the output shaft.

When specified, it necessarily requires the installation of a forced lubrication system, selected from those available for the gearbox, as illustrated in the relevant section of this catalogue.

At scheduled intervals, check and refill the grease in the vane underneath the output shaft's bottom bearing.


Option cannot be specified along with variant LAB -labyrinth seals-.

The chart shows the applicability for the drywell depending on the input and output configurations.

	<b>LR</b>	<b>DR</b>	<b>LD</b>	<b>DD</b>	<b>LL</b>	<b>DL</b>
<b>LP</b>	VP GR	VP GR	VP GR GL	VP GR GL	AD	AD
<b>H</b>	VP GR	—	VP GR GL	—	AD	—
<b>S</b>	VP GR	—	VP GR GL	—	AD	—


The drywell is NOT available for the gear ratios listed here under:

<b>DW</b>	<b>HDP 60</b>	<b>HDP 70</b>	<b>HDP 80</b>	<b>HDP 90</b>
i =	17.3 19.4 43.7 49.1 87.6 98.4	19.4 22.6 49.1 57.0 98.5 114.4	-	20.4 22.4 65.8 73.3 98.9 110.1




## 2.5.8 FIXING ELEMENTS

For shaft-mounted installations, a torque arm from fabricated steel is provided, complete with vibration dampening rubber bushing. Specify the **TA** option.



	<b>A</b>	<b>B</b>	<b>C</b>	<b>D</b>	<b>E</b>	<b>F</b>	<b>R</b>
<b>HDP 60_TA</b>	40	47	32	76	251	340	47
<b>HDP 70_TA</b>	40	47	32	76	251	375	47
<b>HDP 80_TA</b>	60	60	42	97	297	400	60
<b>HDP 90_TA</b>	60	68	42	113	338	460	68



## 2.5.9 CERTIFICATES

### AC - Certificate of compliance

The document certifies the compliance of the product with the purchase order and the construction in conformity with the applicable procedures of the Bonfiglioli Quality System.

### CC - Inspection certificate


The document entails checking on order compliance, the visual inspection of external conditions and of mating dimensions. Checking on main functional parameters in unloaded conditions is also performed along with oil seal proofing, both in static and in running conditions.  
Units inspected are sampled within the shipping batch and marked individually.

### CT - Type certificate

Further to the activities relevant to the Inspection certificate the following checks are also conducted:

- noise
- surface temperature
- tightness of external hardware
- functionality of ancillary devices, if fitted

All checks are conducted with the gear unit running unloaded. Units inspected are sampled within the shipping batch and marked individually.




### 3 GEARBOX RATING CHARTS

#### 3.1 HDP 60

i	n <sub>1</sub> = 1400 min <sup>-1</sup>			n <sub>1</sub> = 1100 min <sup>-1</sup>			n <sub>1</sub> = 900 min <sup>-1</sup>			n <sub>1</sub> = 500 min <sup>-1</sup>		
	Mn <sub>2</sub> [Nm]	Pn <sub>1</sub> [kW]	Rn <sub>1</sub> [N]	Mn <sub>2</sub> [Nm]	Pn <sub>1</sub> [kW]	Rn <sub>1</sub> [N]	Mn <sub>2</sub> [Nm]	Pn <sub>1</sub> [kW]	Rn <sub>1</sub> [N]	Mn <sub>2</sub> [Nm]	Pn <sub>1</sub> [kW]	Rn <sub>1</sub> [N]
HDP 602_7.1	4200	90	3200	4500	76	3510	4600	63	4490	4650	35	4510
HDP 602_8.0	4200	80	4510	4200	63	4510	4200	51	4510	4300	29	4510
HDP 602_9.0	4500	77	-	4600	62	2100	4600	50	3590	4650	28	4510
HDP 602_10.1	4200	64	4290	4250	51	4510	4250	41	4510	4300	23	4510
HDP 602_11.2	4600	63	3280	4600	49	4510	4650	41	4510	4650	23	4510
HDP 602_12.5	4250	52	4510	4300	41	4510	4300	34	4510	4300	18.7	4510
HDP 602_13.5	4600	52	4510	4650	41	4510	4650	34	4510	4650	18.7	4510
HDP 602_15.2	4300	43	4510	4300	34	4510	4300	28	4510	4300	15.4	4510
HDP 602_17.3	4650	41	1680	4650	32	2950	4650	26	2950	4650	14.7	2950
HDP 602_19.4	4300	34	2950	4300	27	2950	4300	22	2950	4300	12.1	2950
HDP 603_22.7	4350	30	2880	4650	25	3050	4650	21	3050	4650	11.4	3050
HDP 603_25.5	4300	26	3050	4300	21	3050	4300	16.9	3050	4300	9.4	3050
HDP 603_28.2	4650	26	3050	4650	20	3050	4650	16.5	3050	4650	9.2	3050
HDP 603_31.7	4300	21	3050	4300	16.6	3050	4300	13.6	3050	4300	7.5	3050
HDP 603_34.2	4650	21	3050	4650	16.6	3050	4650	13.6	3050	4650	7.6	3050
HDP 603_38.5	4300	17.4	3050	4300	13.7	3050	4300	11.2	3050	4300	6.2	3050
HDP 603_43.7	4650	16.6	3050	4650	13.0	3050	4650	10.7	3050	4650	5.9	3050
HDP 603_49.1	4300	13.6	3050	4300	10.7	3050	4300	8.8	3050	4300	4.9	3050
HDP 603_56.6	4650	12.8	2130	4650	10.1	2130	4650	8.2	2130	4650	4.6	2130
HDP 603_63.6	4300	10.5	2130	4300	8.3	2130	4300	6.8	2130	4300	3.8	2130
HDP 603_68.6	4650	10.6	2130	4650	8.3	2130	4650	6.8	2130	4650	3.8	2130
HDP 603_77.1	4300	8.7	2130	4300	6.8	2130	4300	5.6	2130	4300	3.1	2130
HDP 603_87.6	4650	8.3	2130	4650	6.5	2130	4650	5.3	2130	4650	3.0	2130
HDP 603_98.4	4300	6.8	2130	4300	5.3	2130	4300	4.4	2130	4300	2.4	2130

#### 3.2 HDP 70

i	n <sub>1</sub> = 1400 min <sup>-1</sup>			n <sub>1</sub> = 1100 min <sup>-1</sup>			n <sub>1</sub> = 900 min <sup>-1</sup>			n <sub>1</sub> = 500 min <sup>-1</sup>		
	Mn <sub>2</sub> [Nm]	Pn <sub>1</sub> [kW]	Rn <sub>1</sub> [N]	Mn <sub>2</sub> [Nm]	Pn <sub>1</sub> [kW]	Rn <sub>1</sub> [N]	Mn <sub>2</sub> [Nm]	Pn <sub>1</sub> [kW]	Rn <sub>1</sub> [N]	Mn <sub>2</sub> [Nm]	Pn <sub>1</sub> [kW]	Rn <sub>1</sub> [N]
HDP 702_8.0	5450	103	3470	5850	87	3760	6200	76	4040	6200	42	4510
HDP 702_9.3	5650	92	4510	6050	78	4510	6250	66	4510	6350	37	4510
HDP 702_10.1	5850	89	-	6300	75	-	6550	64	1300	6550	35	4510
HDP 702_11.7	6050	79	3470	6250	64	4510	6300	53	4510	6350	30	4510
HDP 702_12.6	6300	77	2190	6550	63	3240	6550	51	4510	6550	28	4510
HDP 702_14.6	6250	65	4510	6300	52	4510	6350	43	4510	6350	24	4510
HDP 702_15.2	6500	65	3380	6550	52	4510	6550	42	4510	6550	23	4510
HDP 702_17.7	6300	54	4510	6350	43	4510	6350	35	4510	6350	19.6	4510
HDP 702_19.4	6550	51	1730	6550	40	2950	6550	33	2950	6550	18.4	2950
HDP 702_22.6	6350	43	2950	6350	34	2950	6350	28	2950	6350	15.3	2950
HDP 703_25.5	6550	40	1790	6550	31	2800	6550	26	3050	6550	14.3	3050
HDP 703_29.6	6350	33	3050	6350	26	3050	6350	21	3050	6350	11.9	3050
HDP 703_31.7	6400	31	2500	6550	25	3050	6550	21	3050	6550	11.5	3050
HDP 703_36.9	6350	27	3050	6350	21	3050	6350	17.3	3050	6350	9.6	3050
HDP 703_38.5	6550	26	3050	6550	21	3050	6550	17.0	3050	6550	9.5	3050
HDP 703_44.7	6350	22	3050	6350	17.4	3050	6350	14.2	3050	6350	7.9	3050
HDP 703_49.1	6550	21	3050	6550	16.3	3050	6550	13.3	3050	6550	7.4	3050
HDP 703_57.0	6350	17.3	3050	6350	13.6	3050	6350	11.1	3050	6350	6.2	3050
HDP 703_63.7	6500	15.9	2130	6550	12.6	2130	6550	10.3	2130	6550	5.7	2130
HDP 703_73.9	6350	13.4	2130	6350	10.5	2130	6350	8.6	2130	6350	4.8	2130
HDP 703_77.2	6550	13.2	2130	6550	10.4	2130	6550	8.5	2130	6550	4.7	2130
HDP 703_89.6	6350	11.0	2130	6350	8.7	2130	6350	7.1	2130	6350	3.9	2130
HDP 703_98.5	6550	10.4	2130	6550	8.1	2130	6550	6.7	2130	6550	3.7	2130
HDP 703_114.4	6350	8.6	2130	6350	6.8	2130	6350	5.6	2130	6350	3.1	2130




### 3.3 HDP 80

i	n <sub>1</sub> = 1400 min <sup>-1</sup>			n <sub>1</sub> = 1100 min <sup>-1</sup>			n <sub>1</sub> = 900 min <sup>-1</sup>			n <sub>1</sub> = 500 min <sup>-1</sup>		
	Mn <sub>2</sub> [Nm]	Pn <sub>1</sub> [kW]	Rn <sub>1</sub> [N]	Mn <sub>2</sub> [Nm]	Pn <sub>1</sub> [kW]	Rn <sub>1</sub> [N]	Mn <sub>2</sub> [Nm]	Pn <sub>1</sub> [kW]	Rn <sub>1</sub> [N]	Mn <sub>2</sub> [Nm]	Pn <sub>1</sub> [kW]	Rn <sub>1</sub> [N]
HDP 802_8.1	9500	180	3980	10250	152	4160	10350	126.0	4960	10350	70	4960
HDP 802_9.4	9850	161	4960	10550	135	4960	11250	117.9	4960	11450	67	4960
HDP 802_9.8	10150	157	3220	10950	133	3430	11350	113.1	4490	11350	63	4960
HDP 802_11.4	10550	141	4960	11300	119	4960	11350	97.5	4960	11450	55	4960
HDP 802_12.6	11050	134	2500	11450	109	4160	11500	89.6	4960	11500	50	4960
HDP 802_14.6	11300	118	4960	11400	93	4960	11450	76.8	4960	11450	43	4960
HDP 802_15.5	11450	113	4640	11500	89	5530	11500	72.9	5530	11500	40	5530
HDP 802_18.0	11350	96	5530	11450	76	5530	11450	62.5	5530	11450	35	5530
HDP 802_19.4	11500	90	5530	11500	71	5530	11500	58.0	5530	11500	32	5530
HDP 802_22.6	11450	77	5530	11450	61	5530	11450	49.8	5530	11450	28	5530
HDP 803_25.8	9900	60	3420	9900	47	4810	9900	38.4	5830	9900	21	5830
HDP 803_30.0	11450	60	3480	11450	47	4870	11450	38.3	5830	11450	21	5830
HDP 803_31.7	11000	54	4860	11500	44	5590	11500	36.3	5830	11500	20	5830
HDP 803_36.8	11450	48	5830	11450	38	5830	11450	31.1	5830	11450	17.3	5830
HDP 803_39.8	11500	45	5830	11500	35	5830	11500	28.9	5830	11500	16.1	5830
HDP 803_46.2	11450	39	5830	11450	30	5830	11450	24.8	5830	11450	13.8	5830
HDP 803_51.6	11500	35	4060	11500	27	5310	11500	22.3	6360	11500	12.4	6400
HDP 803_59.9	11450	30	5770	11450	23	6400	11450	19.1	6400	11450	10.6	6400
HDP 803_64.8	11500	28	6400	11500	22	6400	11500	17.8	6400	11500	9.9	6400
HDP 803_75.2	11450	24	6400	11450	18.6	6400	11450	15.2	6400	11450	8.5	6400
HDP 803_76.4	11500	23	1200	11500	18.4	1690	11500	15.1	2130	11500	8.4	3030
HDP 803_88.7	11450	20	1970	11450	15.8	2460	11450	12.9	2890	11450	7.2	3030
HDP 803_95.9	11500	18.7	2290	11500	14.7	2780	11500	12.0	3030	11500	6.7	3030
HDP 803_111.4	11450	16.0	2900	11450	12.6	3030	11450	10.3	3030	11450	5.7	3030

### 3.4 HDP 90

i	n <sub>1</sub> = 1400 min <sup>-1</sup>			n <sub>1</sub> = 1100 min <sup>-1</sup>			n <sub>1</sub> = 900 min <sup>-1</sup>			n <sub>1</sub> = 500 min <sup>-1</sup>		
	Mn <sub>2</sub> [Nm]	Pn <sub>1</sub> [kW]	Rn <sub>1</sub> [N]	Mn <sub>2</sub> [Nm]	Pn <sub>1</sub> [kW]	Rn <sub>1</sub> [N]	Mn <sub>2</sub> [Nm]	Pn <sub>1</sub> [kW]	Rn <sub>1</sub> [N]	Mn <sub>2</sub> [Nm]	Pn <sub>1</sub> [kW]	Rn <sub>1</sub> [N]
HDP 902_7.9	12500	241	4210	13450	206	4590	14000	173	5770	14000	96	6340
HDP 902_8.8	13100	227	6340	14050	191	6340	14950	166	6340	15250	94	6340
HDP 902_10.1	13550	206	4160	14600	174	4390	15500	151	4650	16550	90	6340
HDP 902_11.2	14200	194	6340	15050	161	6340	15150	133	6340	15250	74	6340
HDP 902_12.2	14350	179	5940	15450	152	6320	16400	132	6340	16550	74	6340
HDP 902_13.6	15050	169	6340	15150	134	6340	15250	110	6340	15250	61	6340
HDP 902_15.8	15350	148	5940	16500	125	6340	16550	103	6340	16550	57	6340
HDP 902_17.6	15150	131	6340	15250	104	6340	15250	85	6340	15250	47	6340
HDP 902_20.1	16450	125	6340	16550	99	6340	16550	81	6340	16550	45	6340
HDP 902_22.4	15250	104	6340	15250	82	6340	15250	67	6340	15250	37	6340
HDP 903_25.4	15600	96	6110	16550	80	6110	16550	65	6110	16550	36	6110
HDP 903_28.3	15250	84	6110	15250	66	6110	15250	54	6110	15250	30	6110
HDP 903_32.9	16550	78	6110	16550	62	6110	16550	50	6110	16550	28.0	6110
HDP 903_36.6	15250	65	6110	15250	51	6110	15250	42	6110	15250	23.2	6110
HDP 903_40.0	16150	63	2370	16550	51	3470	16550	41	4750	16550	23.0	6110
HDP 903_44.6	15250	53	4920	15250	42	6110	15250	34	6110	15250	19.0	6110
HDP 903_51.8	16550	50	5720	16550	39	6110	16550	32	6110	16550	17.8	6110
HDP 903_57.7	15250	41	6110	15250	32	6110	15250	26.5	6110	15250	14.7	6110
HDP 903_65.8	16550	39	6110	16550	31	6110	16550	25.2	6110	16550	14.0	6110
HDP 903_73.3	15250	32	6110	15250	26	6110	15250	20.8	6110	15250	11.6	6110
HDP 903_77.8	16550	33	2050	16550	26	3390	16550	21.3	3680	16550	11.8	3680
HDP 903_86.6	15250	27	3680	15250	22	3680	15250	17.6	3680	15250	9.8	3680
HDP 903_98.9	16550	26	3680	16550	21	3680	16550	16.8	3680	16550	9.3	3680
HDP 903_110.1	15250	22	3680	15250	17.0	3680	15250	13.9	3680	15250	7.7	3680



### 3.5 PERMITTED OVERHUNG LOADS ON OUTPUT SHAFT

#### 3.5.1 HDP 60


**h** : expected lifetime [hours] for bearing of the output shaft

		Rn <sub>2</sub> [kN]						
		LR	LD	RL	RD	DL	DR	DD
input = VP,GL,GR		↔	↔	↔	↔	↔	↔	↔
input = AD		↔	↔	↔	↔	↔	↔	↔
n <sub>2</sub> × h		M <sub>2</sub> = 4300 Nm	M <sub>2</sub> = 3400 Nm	M <sub>2</sub> = 2850 Nm	M <sub>2</sub> = 2150 Nm			
250 000	→	34.4	35.0	35.0	35.0	35.0	35.0	
	←	32.0	35.0	34.1	35.0		35.0	
500 000	→	25.0	29.9	28.1	32.0	29.1	32.9	
	←	24.2	28.0	26.2	30.1	27.5	31.3	
750 000	→	19.9	24.4	23.9	27.6	25.2	28.6	
	←	20.3	23.7	22.3	25.7	23.6	27.0	
1 000 000	→	16.5	20.8	20.7	24.7	22.7	25.8	
	←	17.8	20.9	19.8	23.0	21.1	22.7	
1 250 000	→	14.0	18.1	18.4	22.2	20.8	22.1	
	←	15.1	19.0	18.1	21.0	19.3	20.9	
2 500 000	→		10.5	11.9	15.1	14.5	17.6	
	←		11.2	12.8	15.6	14.5	16.8	
3 750 000	→			8.4	11.4	11.3	14.1	
	←			9.0	12.4	12.1	14.2	
5 000 000	→				9.0	9.2	12.5	
	←				9.6	9.9	12.1	
							14.0	

		Rn <sub>2</sub> [kN]					
		LL	RR	DL	DR	DD	
input = VP,GL,GR		↔	↔	↔	↔	↔	
input = AD		↔	↔	↔	↔	↔	
n <sub>2</sub> × h		M <sub>2</sub> = 4300 Nm	M <sub>2</sub> = 3400 Nm	M <sub>2</sub> = 2850 Nm	M <sub>2</sub> = 2150 Nm		
250 000	→	27.6	32.3	30.6	35.0	32.4	35.0
	←	25.1	29.9	28.6	33.3	30.7	35.0
500 000	→	19.8	23.6	22.7	26.6	24.5	28.4
	←	17.3	21.1	20.8	24.6	22.9	26.7
750 000	→	15.9	19.3	18.8	22.2	20.6	24.0
	←	13.4	16.8	16.9	20.3	19.0	22.4
1 000 000	→	13.4	16.5	16.4	19.5	18.2	21.3
	←	10.9	14.0	14.4	17.5	16.5	19.7
1 250 000	→	11.6	14.5	14.6	17.5	16.4	19.3
	←	9.1	12.1	12.6	15.5	14.7	17.7
2 500 000	→		9.1	9.7	12.1	11.5	13.9
	←		6.7	7.8	10.1	9.9	12.3
3 750 000	→			7.3	9.4	9.1	11.2
	←			5.4	7.5	7.5	9.6
5 000 000	→				7.7	7.6	9.5
	←				5.8	6.0	9.9
						7.9	8.7
							10.6

Shaft the rated overhung load is applicable to. For double extended shaft the load is only applicable to the extension highlighted. Should this not be the case consult Bonfiglioli's Technical Service.

Rated overhung loads relevant to reinforced bearings type HDB.



### 3.5.2 HDP 70


**h** : expected lifetime [hours] for bearing of the output shaft

Rn <sub>2</sub> [kN]							
input = VP,GL,GR							
input = AD							
<b>n<sub>2</sub> × h</b>		<b>M<sub>2</sub> = 6350 Nm</b>		<b>M<sub>2</sub> = 5050 Nm</b>		<b>M<sub>2</sub> = 4200 Nm</b>	
250 000	→	35.2	40.0	37.2	40.0	38.1	40.0
	←	32.8	40.0	34.8	40.0	36.1	40.0
500 000	→	25.1	34.5	28.9	37.0	30.1	37.9
	←	24.8	32.7	26.8	34.7	28.1	36.0
750 000	→	20.0	28.5	23.9	32.1	26.1	33.1
	←	20.8	27.9	22.8	29.8	24.2	31.1
1 000 000	→	16.5	24.6	20.7	28.3	23.2	30.0
	←	17.8	24.8	20.3	26.7	21.6	28.0
1 250 000	→	13.0	21.8	18.4	25.5	20.9	27.7
	←	15.1	22.5	18.4	24.5	19.8	25.8
2 500 000	→		12.7	11.2	18.0	14.6	20.5
	←		14.7	12.6	18.5	14.8	19.7
3 750 000	→				14.1	11.4	16.7
	←		10.0		15.1	12.2	14.6
5 000 000	→				11.0		12.7
	←				12.3		17.3
						14.8	12.4
							16.4

Rn <sub>2</sub> [kN]							
input = VP,GL,GR							
input = AD							
<b>n<sub>2</sub> × h</b>		<b>M<sub>2</sub> = 6350 Nm</b>		<b>M<sub>2</sub> = 5050 Nm</b>		<b>M<sub>2</sub> = 4200 Nm</b>	
250 000	→	26.0	35.7	29.4	39.1	31.6	40.0
	←	23.1	32.8	27.1	36.8	29.7	39.4
500 000	→	18.0	25.9	21.4	29.3	23.6	31.5
	←	15.1	23.0	19.1	27.0	21.7	29.6
750 000	→	14.0	21.0	17.4	24.4	19.7	26.6
	←	11.1	18.1	15.1	22.1	17.7	24.7
1 000 000	→	11.4	17.9	14.9	21.3	17.1	23.5
	←		15.0	12.6	19.0	15.2	21.6
1 250 000	→		15.7	13.0	19.1	15.3	21.3
	←		12.8	10.7	16.8	13.4	19.4
2 500 000	→		9.7		13.0	10.3	15.2
	←		6.7		10.7		13.3
3 750 000	→				10.0		12.2
	←				7.7		10.3
5 000 000	→				8.1		10.3
	←				5.8		13.0
						8.4	11.6

Shaft the rated overhung load is applicable to. For double extended shaft the load is only applicable to the extension highlighted.  
Should this not be the case consult Bonfiglioli's Technical Service.

Rated overhung loads relevant to reinforced bearings type HDB.



### 3.5.3 HDP 80


**h** : expected lifetime [hours] for bearing of the output shaft

Rn <sub>2</sub> [kN]							
input = VP,GL,GR		LR	LD	RL	RD	DL	DR
input = AD		LL	RR	DL	DR		
<b>n<sub>2</sub> × h</b>		<b>M<sub>2</sub> = 11450 Nm</b>	<b>M<sub>2</sub> = 9150 Nm</b>	<b>M<sub>2</sub> = 7600 Nm</b>	<b>M<sub>2</sub> = 5700 Nm</b>		
250 000		39.3 37.1	46.0 46.0	43.7 40.3	46.0 46.0	45.3 42.4	46.0 46.0
500 000		26.0 27.1	41.7 39.9	32.3 30.3	46.0 43.1	35.3 32.5	46.0 45.2
750 000		16.7 20.0	33.5 33.5	25.8 25.4	39.3 36.7	29.8 27.5	41.6 38.8
1 000 000		10.4 14.8	28.1 29.4	21.5 22.2	34.2 32.6	25.8 24.4	37.6 34.7
1 250 000			24.2 25.7	17.8 19.5	30.5 29.7	22.8 22.1	34.3 31.8
2 500 000			10.1 13.0		20.0 21.3	13.5 15.2	19.7 23.9
3 750 000					13.8 15.3		15.7 19.9
5 000 000					9.0 7.1		13.1 11.0
					11.2		13.6 11.3
							20.0 8.5

Rn <sub>2</sub> [kN]							
input = VP,GL,GR		LL	RR	DL	DR	DD	
input = AD		LR	RL	DL	DR		
<b>n<sub>2</sub> × h</b>		<b>M<sub>2</sub> = 11450 Nm</b>	<b>M<sub>2</sub> = 9150 Nm</b>	<b>M<sub>2</sub> = 7600 Nm</b>	<b>M<sub>2</sub> = 5700 Nm</b>		
250 000		27.5 23.3	43.6 39.4	32.6 29.2	46.0 45.2	36.1 33.3	46.0 46.0
500 000		17.5 13.3	30.7 26.5	22.7 19.3	35.7 32.4	26.1 23.3	39.1 36.3
750 000		12.6 8.4	24.3 20.1	17.7 14.4	29.3 26.0	21.2 18.3	32.7 29.9
1 000 000			20.2 16.1	14.5 11.2	25.3 21.9	18.0 15.2	28.6 25.8
1 250 000			17.3 13.1	12.3 9.0	22.3 19.0	15.7 13.0	25.7 22.9
2 500 000			9.4 5.2		14.4 11.0		17.8 15.0
3 750 000					10.4 7.1		13.8 11.0
5 000 000							11.3 8.5
							15.4 13.4

Shaft the rated overhung load is applicable to. For double extended shaft the load is only applicable to the extension highlighted.  
Should this not be the case consult Bonfiglioli's Technical Service.

Rated overhung loads relevant to reinforced bearings type HDB.



### 3.5.4 HDP 90


**h** : expected lifetime [hours] for bearing of the output shaft

Rn <sub>2</sub> [kN]							
input = VP,GL,GR		LR	LD	RL	RD	DL	DR
input = AD		LL	RR	DL	DR		
<b>n<sub>2</sub> × h</b>		<b>M<sub>2</sub> = 15250 Nm</b>		<b>M<sub>2</sub> = 12200 Nm</b>		<b>M<sub>2</sub> = 10150 Nm</b>	
250 000		49.1	62.0	56.9	62.0	61.5	62.0
500 000		50.3	62.0	54.4	62.0	57.1	62.0
750 000		31.9	52.0	40.4	60.7	45.7	62.0
1 000 000		34.9	53.4	41.1	57.9	43.8	50.5
1 250 000		23.0	40.7	32.0	49.9	37.5	55.5
1 500 000		25.0	44.3	34.5	49.2	37.3	43.9
2 500 000		17.0	33.3	26.5	42.8	32.1	38.7
3 750 000		18.3	36.2	28.9	43.7	33.1	36.4
5 000 000		27.9	22.4	37.6	28.3	43.7	35.0
7 500 000		30.2	24.4	39.6	30.1	42.7	49.8
1 000 000		11.9		23.3	17.5	29.8	24.7
1 250 000		12.1		25.2	19.0	31.9	25.2
1 500 000				15.6		22.8	19.5
2 500 000				16.7		24.7	21.2
3 750 000						18.1	16.1
5 000 000						19.6	26.2
7 500 000						17.6	26.8

Rn <sub>2</sub> [kN]							
input = VP,GL,GR		LL	RR	DL	DR	DD	
input = AD		LR	RL	DL	DR		
<b>n<sub>2</sub> × h</b>		<b>M<sub>2</sub> = 15250 Nm</b>		<b>M<sub>2</sub> = 12200 Nm</b>		<b>M<sub>2</sub> = 10150 Nm</b>	
250 000		40.7	62.0	46.7	62.0	50.7	62.0
500 000		33.0	54.4	40.5	62.0	45.6	62.0
750 000		27.5	44.5	33.5	50.8	37.5	54.9
1 000 000		19.7	37.0	27.3	44.7	32.3	49.9
1 250 000		20.9	35.8	26.9	42.1	30.9	46.3
1 500 000		13.1	28.3	20.7	36.0	25.7	41.3
2 500 000		16.4	30.3	22.7	36.5	26.7	40.7
3 750 000		8.9	22.7	16.5	30.5	21.5	35.7
5 000 000		26.3	19.7	32.5	23.7	36.8	28.7
7 500 000		18.7	13.5	26.5	18.5	33.3	24.8
1 000 000				21.7	15.5	25.9	20.5
1 250 000				15.7	10.3	20.9	16.6
1 500 000				14.8		20.6	16.4
2 500 000				10.3		15.5	25.8
3 750 000						12.6	22.0
5 000 000						17.1	22.4
7 500 000						12.1	18.6

Shaft the rated overhung load is applicable to. For double extended shaft the load is only applicable to the extension highlighted.  
Should this not be the case consult Bonfiglioli's Technical Service.

Rated overhung loads relevant to reinforced bearings type HDB.



### 3.6 PERMITTED THRUST LOAD ON OUTPUT SHAFT

#### 3.6.1 HDP 60

input = VP, GL, GR									
input = AD									


↔↔ direction of rotation of output shaft

↑↓ direction of application of axial force

		An <sub>2</sub> [kN]							
n <sub>2</sub> × h	↔↔	M <sub>2</sub> = 4300 Nm		M <sub>2</sub> = 3400 Nm		M <sub>2</sub> = 2850 Nm		M <sub>2</sub> = 2150 Nm	
250 000	a	17.5		17.5		17.5		17.5	
	b	17.5		17.5		17.5		17.5	
	c	17.5		17.5		17.5		17.5	
	d	17.5		17.5		17.5		17.5	
500 000	a	17.5		17.5		17.5		17.5	
	b	17.5		17.5		17.5		17.5	
	c	17.5		17.5		17.5		17.5	
	d	17.5		17.5		17.5		17.5	
750 000	a	16.5	17.5	17.5		17.5		17.5	
	b	17.5		17.5		17.5		17.5	
	c	15.7	17.5	17.5		17.5		17.5	
	d	17.5		17.5		17.5		17.5	
1 000 000	a	13.4	17.3	17.5		17.5		17.5	
	b	17.5		17.5		17.5		17.5	
	c	12.6	16.6	17.3		17.5		17.5	
	d	17.5		17.5		17.5		17.5	
1 250 000	a	11.1	14.8	15.6	17.5	17.5		17.5	
	b	17.5		17.5		17.5		17.5	
	c	10.3	14.0	15.0	17.5	17.5		17.5	
	d	17.5		17.5		17.5		17.5	
2 500 000	a	4.9	7.9	9.5	12.5	12.2	15.3	15.8	17.5
	b	17.5		17.5		17.5		17.5	
	c	4.1	7.1	8.8	11.9	11.7	14.7	15.4	17.5
	d	17.5		17.5		17.5		17.5	
3 750 000	a		4.5	6.4	9.1	9.2	11.9	12.7	15.4
	b	17.5		17.5		17.5		17.5	
	c		3.7	5.8	8.4	8.7	11.3	12.3	15.0
	d	17.5		17.5		17.5		17.5	
5 000 000	a			4.4	6.9	7.2	9.7	10.8	13.2
	b		17.5	17.5		17.5		17.5	
	c			3.8	6.3	6.7	9.2	10.4	12.8
	d		17.5	16.8	17.5	17.5		17.5	



Rated thrust loads relevant to reinforced bearings type HDB.



### 3.6.2 HDP 70


<b>input = VP, GL, GR</b>									
<b>input = AD</b>									

↔↔ direction of rotation of output shaft

↑↓ direction of application of axial force

An <sub>2</sub> [kN]									
n <sub>2</sub> × h	↔↔	M <sub>2</sub> = 6350 Nm		M <sub>2</sub> = 5050 Nm		M <sub>2</sub> = 4200 Nm		M <sub>2</sub> = 3150 Nm	
250 000	a	25.0		25.0		25.0		25.0	
	b	25.0		25.0		25.0		25.0	
	c	25.0		25.0		25.0		25.0	
	d	25.0		25.0		25.0		25.0	
500 000	a	25.0		25.0		25.0		25.0	
	b	25.0		25.0		25.0		25.0	
	c	25.0		25.0		25.0		25.0	
	d	25.0		25.0		25.0		25.0	
750 000	a	20.6	25.0	25.0		25.0		25.0	
	b	25.0		25.0		25.0		25.0	
	c	19.3	25.0	25.0		25.0		25.0	
	d	25.0		25.0		25.0		25.0	
1 000 000	a	16.6	25.0	22.1	25.0	25.0		25.0	
	b	25.0		25.0		25.0		25.0	
	c	15.4	24.9	21.2	25.0	24.9	25.0	25.0	
	d	25.0		25.0		25.0		25.0	
1 250 000	a	13.8	22.7	19.3	25.0	22.9	25.0	25.0	
	b	25.0		25.0		25.0		25.0	
	c	12.6	21.5	18.3	25.0	22.1	25.0	25.0	
	d	25.0		25.0		25.0		25.0	
2 500 000	a	6.2	13.5	11.7	18.9	15.3	22.4	19.7	25.0
	b	24.0	25.0	25.0		25.0		25.0	
	c	4.9	12.3	10.7	17.9	14.5	21.6	19.1	25.0
	d	22.3	25.0	24.5	25.0	25.0		25.0	
3 750 000	a		8.9	7.9	14.3	11.5	17.8	15.9	22.2
	b		25.0	22.1	25.0	23.3	25.0	24.8	25.0
	c		7.7	6.9	13.4	10.7	17.0	15.3	21.6
	d		25.0	20.7	25.0	22.2	25.0	23.9	25.0
5 000 000	a		6.0	5.5	11.4	9.1	14.9	13.5	19.3
	b		23.9	19.6	25.0	20.8	25.0	22.3	25.0
	c		4.8	4.5	10.4	8.2	14.1	12.9	18.7
	d		22.2	18.3	24.3	19.7	25.0	21.5	25.0

■ Rated thrust loads relevant to reinforced bearings type HDB.



### 3.6.3 HDP 80


input = VP, GL, GR									
input = AD									

↔↔ direction of rotation of output shaft










↑↓ direction of application of axial force

An <sub>2</sub> [kN]							
n <sub>2</sub> × h	↔↔	M <sub>2</sub> = 11450 Nm	M <sub>2</sub> = 9150 Nm	M <sub>2</sub> = 7600 Nm	M <sub>2</sub> = 5700 Nm		
250 000	a	30.0		30.0		30.0	
	b	30.0		30.0		30.0	
	c	30.0		30.0		30.0	
	d	30.0		30.0		30.0	
500 000	a	25.3	30.0	30.0		30.0	
	b	30.0		30.0		30.0	
	c	23.5	30.0	30.0		30.0	
	d	30.0		30.0		30.0	
750 000	a	17.7	30.0	26.0	30.0	30.0	
	b	30.0		30.0		30.0	
	c	15.8	30.0	24.5	30.0	30.0	
	d	30.0		30.0		30.0	
1 000 000	a	12.7	26.8	21.1	30.0	26.8	30.0
	b	30.0		30.0		30.0	
	c	10.9	25.1	19.6	30.0	25.5	30.0
	d	30.0		30.0		30.0	
1 250 000	a	9.2	22.5	17.6	30.0	23.2	30.0
	b	30.0		30.0		30.0	
	c	7.3	20.8	16.1	29.2	22.0	30.0
	d	30.0		30.0		30.0	
2 500 000	a		10.8	8.0	18.8	13.7	24.2
	b		30.0	29.6	30.0	30.0	30.0
	c		9.1	6.5	17.5	12.4	23.1
	d		30.0	27.7	30.0	30.0	30.0
3 750 000	a			13.0	8.9	18.4	15.8
	b		30.0		26.8	30.0	29.3
	c			11.6	7.7	17.3	14.9
	d		29.9		30.0	25.3	28.1
5 000 000	a			9.3	5.9	14.7	12.8
	b			30.0	23.8	30.0	26.2
	c			7.9	4.7	13.6	11.9
	d			29.1	22.2	30.0	25.1

■ Rated thrust loads relevant to reinforced bearings type HDB.



### 3.6.4 HDP 90


<b>input = VP, GL, GR</b>									
<b>input = AD</b>									

↔↔ direction of rotation of output shaft

↑↓ direction of application of axial force

		An <sub>2</sub> [kN]				
n <sub>2</sub> × h	↔↔	M <sub>2</sub> = 15250 Nm	M <sub>2</sub> = 12200 Nm	M <sub>2</sub> = 10150 Nm	M <sub>2</sub> = 7600 Nm	
250 000	a	37.5		37.5		37.5
	b	37.5		37.5		37.5
	c	37.5		37.5		37.5
	d	37.5		37.5		37.5
500 000	a	34.1	37.5	37.5	37.5	37.5
	b	37.5		37.5		37.5
	c	32.2	37.5	37.5	37.5	37.5
	d	37.5		37.5		37.5
750 000	a	23.6	37.3	35.1	37.5	37.5
	b	37.5		37.5		37.5
	c	21.7	35.5	33.5	37.5	37.5
	d	37.5		37.5		37.5
1 000 000	a	16.9	29.8	28.4	37.5	36.1
	b	37.5		37.5		37.5
	c	15.0	28.0	26.8	37.5	34.8
	d	37.5		37.5		37.5
1 250 000	a	12.1	24.3	23.6	35.2	31.3
	b	37.5		37.5		37.5
	c	10.2	22.5	22.0	33.7	30.0
	d	37.5		37.5		37.5
2 500 000	a		9.5	10.5	20.4	18.2
	b		37.5	37.5		37.5
	c		7.8	9.0	19.0	16.9
	d		37.5	37.5		37.5
3 750 000	a			4.1	13.1	11.8
	b		37.5	36.0	37.5	37.5
	c			2.5	11.6	10.5
	d		37.5	33.5	37.5	36.3
5 000 000	a				8.4	7.6
	b				37.5	34.2
	c				7.0	6.3
	d				37.5	32.1

■ Rated thrust loads relevant to reinforced bearings type HDB.




### 3.7 MASS MOMENT OF INERTIA

Moments of inertia are relevant to gear unit's input shaft and to product configuration correspondent to the combination: LP-LR with single-sided input shaft.

$i_N$	$J \cdot 10^{-4}$ [Kg m <sup>2</sup> ]			
	HDP 60	HDP 70	HDP 80	HDP 90
7.1	120	-	-	-
8.0	116	143	335	600
9.0	95	133	314	570
10.0	92	109	263	440
11.2	68	103	248	421
12.5	67	77	183	324
14.0	54	74	175	311
16.0	53	60	132	226
18.0	33	58	127	219
20.0	33	40	99	171
22.4	33	38	95	166
25.0	33	36	85	177
28.0	29	35	83	174
31.5	29	30	68	156
35.5	27	30	67	154
40.0	27	28	67	91
45.0	24	27	66	90
50.0	24	25	44	82
56.0	11	25	44	82
63.0	11	12	41	77
71.0	11	12	41	77
80.0	11	11	21	39
90.0	10	11	21	38
100.0	10	10	20	36
112.0	-	10	20	36



### 3.8 EXACT RATIOS

$i_N$	HDP 60	HDP 70	HDP 80	HDP 90
7.1	7.146			
8.0	8.031	8.039	8.063	7.929
9.0	8.969	9.333	9.361	8.828
10.0	10.079	10.090	9.844	10.059
11.2	11.156	11.714	11.429	11.200
12.5	12.538	12.551	12.600	12.214
14.0	13.533	14.571	14.629	13.600
16.0	15.209	15.225	15.488	15.807
18.0	17.267	17.676	17.981	17.600
20.0	19.404	19.425	19.441	20.086
22.4	22.686	22.552	22.571	22.364
25.0	25.494	25.521	25.800	25.406
28.0	28.219	29.630	29.954	28.288
31.5	31.713	31.746	31.713	32.878
35.5	34.231	36.857	36.818	36.608
40.0	38.470	38.510	39.809	40.036
45.0	43.675	44.710	46.218	44.578
50.0	49.082	49.134	51.625	51.811
56.0	56.578	57.044	59.937	57.689
63.0	63.583	63.650	64.805	65.837
71.0	68.633	73.898	75.238	73.306
80.0	77.131	77.213	76.405	77.818
90.0	87.567	89.644	88.706	86.646
100.0	98.408	98.513	95.911	98.884
112.0	-	114.373	111.352	110.102





## 4 DIMENSIONS AND WEIGHT

### 4.1 HDP 60





**VP**

VP	i	A	B	C	D	E	F	Kg
HDP 60_2	7.1 ... 15.2	38 k6	10	41	M12x28	70	80	161
HDP 60_2	17.3 ... 19.4	32 k6	10	35	M12x28	70	80	161
HDP 60_3	22.7 ... 49.1	32 k6	10	35	M12x28	70	80	164
HDP 60_3	56.6 ... 98.4	28 j6	8	31	M10x22	50	60	164









**AD**


AD	M	M1	M2	N	N1	N2	N3	N4	X	P
HDP 60_112	28	31.3	8	250	215	180	15	14	5	220
HDP 60_132	38	41.3	10	300	265	230	16	14	5	230
HDP 60_160	42	45.3	12	350	300	250	23	18	6	261
HDP 60_180	48	51.8	14	350	300	250	23	18	6	261





**GL  
GR**

GL / GR	M	M1	M2	N	N1	N2	N3	N4	X	P
HDP 60_132	38	41.3	10	300	265	230	16	14	5	311
HDP 60_160	42	45.3	12	350	300	250	23	18	6	341
HDP 60_180	48	51.8	14	350	300	250	23	18	6	341
HDP 60_200	55	59.3	16	400	350	300	-	M16x23	7	366
HDP 60_225	60	64.4	18	450	400	350	25	18	7	374

**LP****H****S****F...**




## 4.2 HDP 70




VP

VP	i	A	B	C	D	E	F	Kg
HDP 70 2	8.0 ... 17.7	38 k6	10	41	M12x28	70	80	189
HDP 70 2	19.4 ... 22.6	32 k6	10	35	M12x28	70	80	189
HDP 70 3	25.5 ... 57.0	32 k6	10	35	M12x28	70	80	192
HDP 70 3	63.7 ... 114.4	28 j6	8	31	M10x22	50	60	192









AD

AD	M	M1	M2	N	N1	N2	N3	N4	X	P
HDP 70_112	28	31.3	8	250	215	180	15	14	5	220
HDP 70_132	38	41.3	10	300	265	230	16	14	5	230
HDP 70_160	42	45.3	12	350	300	250	23	18	6	261
HDP 70_180	48	51.8	14	350	300	250	23	18	6	261
HDP 70_200	55	59.3	16	400	350	300	-	M16x23	7	286


GL  
GR

GL / GR	M	M1	M2	N	N1	N2	N3	N4	X	P
HDP 70_132	38	41.3	10	300	265	230	16	14	5	311
HDP 70_160	42	45.3	12	350	300	250	23	18	6	341
HDP 70_180	48	51.8	14	350	300	250	23	18	6	341
HDP 70_200	55	59.3	16	400	350	300	-	M16x23	7	366
HDP 70_225	60	64.4	18	450	400	350	25	18	7	374

**LP****H****S****F...**





### 4.3 HDP 80















VP

VP	i =	A	B	C	D	E	F	$\text{kg}$
HDP 80 2	8.1 ... 14.6	45 k6	14	48.5	M16x36	100	110	301
HDP 80 2	15.5 ... 22.6	38 k6	10	41	M12x28	70	80	301
HDP 80 3	25.8 ... 75.2	38 k6	10	41	M12x28	70	80	306
HDP 80 3	76.4 ... 114.4	28 j6	8	31	M10x22	50	60	306


AD

GL  
GR


**LP****H****S****F...****F550L**



#### 4.4 HDP 90




**VP**




VP	i	A	B	C	D	E	F	Kg
HDP 90_2	7.9 ... 13.6	50 k6	14	53.5	M16x36	100	110	429
HDP 90_2	15.8 ... 22.4	45 k6	14	48.5	M16x36	100	110	429
HDP 90_3	25.4 ... 73.3	45 k6	14	48.5	M16x36	100	110	440
HDP 90_3	77.8 ... 110.1	32 k6	10	35	M12x28	70	80	440

**AD**




AD	M	M1	M2	N	N1	N2	N3	N4	X	P
HDP 90_160	42	45.3	12	350	300	250	23	18	6	308.5
HDP 90_180	48	51.8	14	350	300	250	23	18	6	308.5
HDP 90_200	55	59.3	16	400	350	300	-	M16x23	7	333.5



**GL  
GR**





GL / GR	M	M1	M2	N	N1	N2	N3	N4	X	P
HDP 90_160	42	45.3	12	350	300	250	23	18	6	427
HDP 90_180	48	51.8	14	350	300	250	23	18	6	427
HDP 90_200	55	59.3	16	400	350	300	-	M16x23	7	452
HDP 90_225	60	64.4	18	450	400	350	25	18	7	457
HDP 90_250	65	69.4	18	550	500	450	30	18	6	487
HDP 90_280	75	79.9	20	550	500	450	30	18	6	487





LP





H




S




F...








#### 4.5 MANIFOLD FLANGE

Available for shaft arrangement: LL, LR, LD, RL, RR and RD, all featuring a single shaft extension.




	<b>A</b>	<b>B</b>	<b>C</b>	<b>D</b>	<b>E</b>	<b>F</b>	<b>G</b>	<b>H</b>
<b>HDP 60_FM</b>	125	175	208	19	14	21	165	135
<b>HDP 70_FM</b>	125	175	208	19	14	21	195	135
<b>HDP 80_FM</b>	170	212	254	21	20	24	240	166
<b>HDP 90_FM</b>	170	212	254	21	20	24	240	166


#### 4.6 CUSTOMER'S SHAFT series HDP




	<b>A1</b>	<b>A2</b>	<b>A3</b>	<b>B</b>	<b>B1</b>	<b>B2</b>	<b>C</b>	<b>D</b>	<b>E</b>	<b>F</b>	<b>R</b>	<b>S</b>	
<b>HDP 60</b>	≥ 78	70 h6	69	283	56	172	220	30	20 h9	74.5	2.5	2	20 x 12 x 220A
<b>HDP 70</b>	≥ 89	80 h6	79	283	78	127	220	30	22 h9	85	2.5	2.5	22 x 14 x 220A
<b>HDP 80</b>	≥ 104	95 h6	94	338	73	192	280	30	25 h9	100	2.5	2.5	25 x 14 x 280A
<b>HDP 90</b>	≥ 121	110 h6	109	378	88	202	320	30	28 h9	116	2.5	2.5	28 x 16 x 320A



	<b>A1</b>	<b>A2</b>	<b>A3</b>	<b>A4</b>	<b>B</b>	<b>B1</b>	<b>B2</b>	<b>R</b>	<b>S</b>
<b>HDP 60</b>	≥ 90	72 h7	69	70 g6	328	59	194	2.5	2.5
<b>HDP 70</b>	≥ 104	82 h7	79	80 g6	332	77	174	2.5	2.5
<b>HDP 80</b>	≥ 119	97 h7	94	95 g6	398	95	205	2.5	2.5
<b>HDP 90</b>	≥ 136	112 h7	109	110 g6	440	87	273	2.5	2.5





## INDEX OF REVISIONS

R0

DOCUMENT	SECTION	DESCRIPTION
----------	---------	-------------

INDUSTRY PROCESS  
AND AUTOMATION SOLUTIONS



[www.bonfiglioli.com](http://www.bonfiglioli.com)

 **BONFIGLIOLI**